


	Description	Symbol	Colour	State	Description
	Information	i	Blue	Active	The system or sector cannot be activated. Forced activation is possible (errors or open areas can be disabled).
				Flashing	The system or sector cannot be activated or forced into operation (errors or open areas cannot be disabled).
				Inactive	The system or sector cannot be activated.
	User	i	Green	Active	The allocated area has been disabled.
				Flashing	The allocated area is in partial activated A/B.
				Inactive	The allocated sector is under full surveillance.
	Alarm	🔔	Red	Active	Alarm
				Inactive	No alarm
	System	⚠	Orange	Flashing	Error
				Inactive	No error
	Power supply	🔄	Green	Active	System OK
				Flashing	Power failure
				Inactive	No connection to data bus

## Siemens Alarm System



**SAFEHOME**

To activate full surveillance

To activate partial surveillance

To disable surveillance:

**Safe Home SA**

**Rue de Genève 70 - 1004 Lausanne Tél:**

**0848 848 555 Fax: 0848 848 556**

**www.safehome.ch**

Enter code and confirm with the square black key.

Use the key card and confirm with the square black key.

Enter the code and confirm with the black A or B keys.

Use the key card and confirm with the black A or B keys.

Enter the code and confirm with the empty square key.

Use the key card and confirm with the empty square key.

If you enter the wrong code four consecutive times then further attempts will be prohibited for 1 minute.

### Changing codes or key cards:

Enter the code and then press the right arrow. Select User Management from the menu. Add, Edit or Delete.

**Note:** Only Managers Users are authorised to do this.

Without the document entitled "customer data" and your key cards we cannot activate your security system.

Please send them by registered post in a padded envelope to the following address:

**Protectas SA, Impasse Colombelle 8, 1218 Le Grand-Saconnex**